


Stepper Motor Specifications:

MODEL	Phase	Step Angle	Rated Voltage	Current /Phase	Resistance /Phase	Inductance /Phase	Holding Torque	Rotor Inertia
		Deg/Step	V	A	Ω	mH	kg. cm	g. cm^2
57STH56-2804MB	2	0.9	2.52	2.8	0.9	4.5	12	300

Wiring Diagram:



Rotation:

CW Direction	Step	A	C	B	D
↓	1	+		+	
	2		+	+	
	3		+		+
	4	+			+
	1	+		+	

CW Direction, see from the flange side.

REV.	QTY.	No.	SIG.	DATE	3330_0			DONGZHENG MOTOR	
								57STH56-2804MB	
								STEPPER MOTOR	
DESIGN	Zhu Guanghua	2021.11.30	STD.		CLS. MAK	QTY	SCALE	P/N.	REV
CHECK	Xu Weigang	2021.11.30			S		1:1		
PROC.			APPR.		PAGE	OF		ODZ. 253.001	A